Design & Technology AQA GCSE

Paper – 8552/W

2 hours

Materials required for questions

- Pencil
- Rubber
- Calculator

Instructions

- Use black ink or ball-point pen
- Try answer all questions
- Use the space provided to answer questions
- Calculators can be used if necessary
- For the multiple choice questions, circle your answer

Advice

- Marks for each question are in brackets
- Read each question fully
- Try to answer every question
- Don't spend too much time on one question

Good luck!

100 marks

Section A – Core technical principles

Each of Questions 01 to 10 is followed by four responses, A, B, C and D.

For each question circle the appropriate answer.

- **Q1)** What is the primary reason that many renewable energy technologies still depend on finite resources?
 - A They require rare earth elements for magnets and batteries
 - **B** Sunlight and wind are actually finite resources
 - **C** No non-finite resources are needed for their construction
- Q2) How is electricity generated in a nuclear power plant?
 - **A** By burning uranium to produce steam
 - **B** By using nuclear fusion to directly create electricity
 - **C** By splitting uranium atoms to produce heat, which generates steam
- Q3) Why are metal foams valuable in automotive design?
 - A They absorb impact energy while being lightweight
 - **B** They conduct electricity better than copper
 - **C** They change colour under stress

Q4) What material is best for a see-through phone case?					
Α	Acrylic (PMMA)				
В	High impact polystyrene (HIPS)				
С	Polyethylene terephthalate (PET)				
Q5) Which	of the following is not an input for a system?				
Α	Light sensors				
В	Pressure sensors				
С	Timers				
Q6) Which	lever has the fulcrum between the effort and the load?				
Α	First-order lever				
В	Second-order lever				
С	Third-order lever				
Q7) A duct	ile material is commonly described as one that				
Α	Can be drawn into a long length				
В	Does not scratch easily				
С	Resists corrosion and oxidisation				

- Q8) Which scenario exemplifies "market pull"?
 - A A pharmaceutical company developing mRNA technology
 - **B** Consumers demanding longer smartphone battery life
 - **C** Engineers creating a more efficient solar panel
- **Q9)** A company designs a smartphone with non-replaceable batteries to push users to upgrade sooner. Which ethical principle does this violate?
 - A Transparency Failing to disclose the short lifespan
 - **B** User autonomy Removing the right to repair
 - **C** Both of the above
- **Q10)** A person needs to print 400 labels for a product. Each label covers 0.04cm². A roll of labels covers 7cm² and cost £4.99. What is the cost to label all the products?
 - **A** £14.97
 - **B** £9.98
 - **C** £19.96


reciprocating motion in their respective followers.
Eccentric (circular) cam Pear shaped cam Snail cam
a) Describe the characteristic movement each cam generates in its follower
(i) Eccentric (circular) cam (2 marks)
(ii) Pear shaped cam (2 marks)
(iii) Snail cam (2 marks)

Q11) The image shows the profiles of three types of cam which all generate

eeds. (4 marks	eeds. Evaluate the use of nuclear energy for our future energy)
Section B – Spec	cialist technical principles
Q13) Once a tre	e is felled, the timber is usually seasoned before it can be used.
Explain two advoseasoning. (4 m a	antages of using kiln seasoning in preference to natural arks)

14) Describe two ways that a jig can be used to improve accuracy in anufacture. (4 marks)			
) The table iden	tifies specific proces	esos usad to ramava	different materials
	erials are cut to a tol		different materials
ose one process process in detail	from the table and, I. (5 marks)	using notes and/or	sketches, describe
Offset	Casting	Extrusion	Flow soldering
lithography			

Q16.1) Some sheet metal is being cut for a car door. If the density of the metal is 2.8g/cm3 and the metal is 6mm thick. What is the mass of the sheet metal? All measurements are in mm. (4 marks)



Q16.2) The sheet metal costs £4.50 per kg, what is the total material cost for four car door panels. (2 marks)

Q18) One quality control test that would be used during volume production of the sprocket and crank arm is to check dimensional accuracy.



Outline three further quality control checks that could be carried out on the assembled sprocket and crank arm. (3 marks)
Section C – Designing and making principles
Q19) Give four advantages to the manufacturer of internet marketing. (4 marks)
1.
2.
3.

Q22) The image shows the interior of the electric car.



Q22.1) Evaluate the ergonomics of the interior. (4 marks)

Q22.1) Evaluate the aesthetics of the interior. (4 marks)

Q22.1 Evaluate the interior of the var with reference to user needs. (4 marks
22.1 Evaluate the interior of the var with reference to user needs. (4 marks
22.1 Evaluate the interior of the var with reference to user needs. (4 marks
Q22.1 Evaluate the interior of the var with reference to user needs. (4 marks
Q23.1) A designer is creating a cylindrical container for a new product. The container must hold 300 cm ³ of liquid. The radius of the base is 3 cm. Calculate the height of the container. (3 marks)

Q23.2) The designer wraps a label around the side of the can. The label covers the curved surface only.
Calculate the area of one label, then work out the total area needed for 500 cans. (4 marks)
Q24) Choose a designer from of your choice.
Outline the design features and/or manufacturing techniques that have made your chosen designer successful. You should refer to specific products in your answer. (6 marks)

Q25) Designers often collaborate.
Discuss the importance of collaboration in creating effective design solutions.
Give examples to support your answer. (6 marks)
Q26) Give three safety checks which should be made prior to using a pillar drill. (3 marks)
1.
2.

Q27) Identify and explain three features where anthropometrics has been used to inform the design. (3 \times 2 marks)



1.

2.

_			
3.			

END OF PAPER